

**ZONE WIRE CONNECTOR · P2**

# Blue compact wire nut, low profile

Type **Pressure-type wire connector** Color **Blue** Wire range **22–14 AWG**

## PACK LISTINGS

| Pack size | Listing |
|---|---|
| 1000 pcs | UL 486C · 300 V |

## PRINTED BOX-LABEL FACTS

| | | | | | |
|---|---|---|---|---|---|
| Conductors | **Copper to copper** | Temperature | **105°C (221°F) Max** | | |
| Voltage | **300V Max** | Strip | **3/8" (9.5 mm). For #16 and smaller wires, strip 1/2" (12.7 mm)** | | |

## PRODUCT FACTS

| | | | | | |
|---|---|---|---|---|---|
| Flammability | **UL 94V-2** | Material | **Polypropylene (PP)** | | |
| Construction | **Compact low-profile housing with an internal square spring** | | | | |

## PRINTED WIRE COMBINATIONS · Solid and/or stranded

- 1 #14
- 1 to 3 #16
- 1 to 4 #18
- 3 to 5 #20
- 2 #22
- 1 #14 w/1 #16
- 1 #14 w/1 or 2 #18
- 1 #14 w/1 to 3 #20 or #22
- 1 #16 w/1 to 3 #18
- 1 #16 w/1 #18 w/1 #20
- 1 #16 w/1 to 4 #20 or #22
- 1 #16 w/1 #22 w/1 #18 or #20
- 2 #16 w/1 #18
- 2 #16 w/1 or 2 #20
- 2 #16 w/1 #20 w/1 #22
- 2 #16 w/1 to 3 #22
- 1 #18 w/1 to 4 #20 or #22
- 1 or 2 #18 w/1 #20 w/1 #22
- 2 #18 w/1 to 3 #20 or #22
- 3 #18 w/1 or 2 #20 or #22
- 4 #18 w/1 #22
- 3 #20 w/1 or 2 #22
- 4 #20 w/1 #22

## PRINTED STEPS

1. Turn off power before installing or removing connectors.
2. Strip wires 3/8" (9.5 mm). For #16 and smaller wires, strip 1/2" (12.7 mm).
3. Pre-twisting unnecessary, hold stripped wires together with ends even. Lead stranded wires slightly.
4. Align any frayed strands or conductors.
5. Push wires into connector and screw on until two twists are visible in wires.